111111 CISCO

Cisco IP Phone 6861 Multiplatform Phones

Ouick Start Guide

Your Phone



- 1. Incoming call or voicemail indicator
- 2. Line and feature buttons
- 3. Softkeys
- 4. Navigation
- 5. Hold, Transfer, and Conference
- 6. Speakerphone, Headset, and Mute
- 7. Voicemail, Applications, and Directory
- 8. Volume

Line and Feature Buttons

Use the line and feature buttons to view calls on a line, access features such as Speed Dial, and to perform tasks such as resuming a held call.

Buttons illuminate to indicate status:

- Green–Line is idle.
- 🕒 or 🖃 Red, steady–Line is active or in use.
- 🔲 or 🔲 Red, flashing–Line is on hold or there is an inbound call.
- 🔚 or 🔜 Amber, steady–Line is unregistered (cannot be used).

Make a Call

Enter a number and pick up the handset.

Answer a Call

Press the flashing red line button.

Put a Call on Hold

- 1. Press Hold D or Hold.
- To resume a call from hold, press Hold 🛄 or 2. Resume.

View Your Recent Calls

- 1. Select a line to view.
- 2. Select Recents.

Transfer a Call to Another Person

- 1. From a call that is not on hold, press Transfer -1
- 2. Enter the other person's phone number and press Call.
- З. Press Transfer again.

Add Another Person to a Call

- 1. From an active call, press Conference
- Enter the phone number for the party you want to add 2.
- Press Conference again. З.

and press Call.

Make a Call with a Headset

- 1. Plug in a headset.
- Enter a number using the keypad. 2.
- 3. Press Headset





Make a Call with the Speakerphone

- 1. Enter a number using the keypad.
- 2. Press Speakerphone



111111 CISCO

Cisco IP Phone 6861 Multiplatform Phones

Mute Your Call

- Press Mute 1
- 2. Press Mute again to turn mute off.

Listen to Voice Messages

Press Messages and follow the voice prompts. To check messages for a specific line, press the line button first.

Forward All Calls

- Select a line and press Forward all. 1.
- 2. Dial the number that you want to forward, or press Voicemail.
- When you return, press Clr fwd all. З.

Adjust the Volume During a Call

Press Volume up and down to adjust the volume while you are on a call.

Adjust the Phone Ringer Volume

Press Volume 🛄 up and down to adjust the ringer volume when the phone rings or when the phone is not in use.

Change the Ringtone

- Press Applications 1.
- 2. Select User preferences > Ringtone > Ext (n) -Ring tone, where n= extension number.
- Scroll through the list of ringtones and press Play to hear a sample.
- Press Select and then Set to save a selection.

Adjust the Phone Screen Contrast

- Press Applications 1
- 2. Select User preferences > Screen preferences > Contrast level.
- З. Press the Navigation cluster up or down to increase or decrease the brightness.
- Press Save. Δ

Set the Backlight Timer

- Press Applications 1.
- Select User preferences > Screen preferences > 2. Backlight timer.
- Press the Select button to scroll through the options and select a timer duration.
- Press Set to apply the selection. 4.

Connect to a Wireless Network

Make sure that your phone isn't connected to a wired network. You can connect the phone to a wireless network either with credentials or WPS. See the User Guide for the connection through WPS.

- 1. Press Applications
- 2. Select Network configuration > Wi-Fi configuration > Wi-Fi profile.
- Press Scan to search for available networks. З.
- 4. Select a network.
- 5. Enter the user ID and password.
- 6. Press Connect.

User Guide

View the full User Guide at https://www.cisco.com/c/en/us/td/docs/voice ip comm/c uipph/MPP/6800/english/userguide/p680 b 6800-userquide-mpp.html

The Cisco-published Microsoft Word and PDF versions of this document contain the features supported by Cisco. Any changes made by customers are not supported by Cisco.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)